

admin 3com switch



switching 3com 4500
password-control length 6
local-user admin

login system-view
password-control length 6
local-user user
local-user xxxx

<4500>sys
System View: return to User View with Ctrl+Z.
[4500]]password-control length 6
[4500]local-user admin
[4500-luser-admin]

s3n03_03_02s56.app
local-user xxxx

2

`cipher` = 密码以密文形式显示

`simple` = 密码以明文形式显示 *密码中不允许包含特殊字符

```
[4500-luser-admin]password ?  
cipher  Display password with cipher text  
simple  Display password with plain text
```

设置密码策略 `admin` 密码为 `abcdef`

```
[4500-luser-admin]password cipher abcdef  
The system failed to assign password. It has been used  
previously.
```

密码策略配置

配置策略 `policy`

```
[4500]password-control ?  
aging          Specify password aging time ->  
[0-31536000]  
alert-before-expire  Specify the alert time before  
password expired -> [0-31536000]  
authentication-timeout Specify the authentication timeout ->  
[0-31536000]  
composition     Specify composition of password ->  
[0-31536000] [0-31536000] [0-31536000] [0-31536000]  
history         Specify maximum history record ->  
[0-31536000] (0-31536000)  
length         Specify minimum length of password ->  
[0-31536000]  
login-attempt   Specify the local user's login
```

attempts -> `login (super user)`
The super user's password controls ->
`super user`

Global password settings for all users:
Password aging: Enabled
Password length: Enabled(6 Characters)
Password composition: Enabled(1 type(s), 1 character(s) per type)
Password history: Enabled(Max history record:4)
Password alert before expire: 7 days
Password authentication-timeout:60 seconds
Password attempt times: 3 times
Password attempt-failed action: Lock for 120 minutes

Global password settings for all users:
Password aging: Enabled
Password length: Enabled(6 Characters)
Password composition: Enabled(1 type(s), 1 character(s) per type)
Password history: Enabled(Max history record:4)
Password alert before expire: 7 days
Password authentication-timeout:60 seconds
Password attempt times: 3 times
Password attempt-failed action: Lock for 120 minutes

```
[4500]undo password-control aging enable  
Password aging disabled for all users.  
[4500]undo password-control composition enable  
Password composition is disabled for all users.  
[4500]undo password-control history enable  
Password history disabled for all users.
```

Global password settings for all users:
Password aging: Enabled
Password length: Enabled(6 Characters)
Password composition: Enabled(1 type(s), 1 character(s) per type)
Password history: Enabled(Max history record:4)
Password alert before expire: 7 days
Password authentication-timeout:60 seconds
Password attempt times: 3 times
Password attempt-failed action: Lock for 120 minutes

admin

[4500]local-user admin

[4500-luser-admin]password cipher abcdef

Updating user password, please wait.....

*** cipher abcdef

R9E#&=!H6Q_QxT77=^Q`MAF4<1!!

[4500-luser-admin]quit

[4500]save

[4500]quit

<4500>quit